



VIVAX VOX

VIVAX

Model : BS-261

Ean code

3856005192052

VIVAX Speaker System BS-261



BT
BLUETOOTH

mp3



DESCRIPTION	
Bluetooth Speaker, USB player; MP3; FM with memory ; AUX LINE in 3,5mm ; USB in; 2x30W RMS Audio output (2x7,6cm speaker, 80Hz-16kHz), Power supply: 3600mAh Rechargeable Battery; Deep and Powerfull Bass, Charging by Micro USB connection, Up to 8 hours Music Play (in moderate volume)/ Up to 3 hours on Max Volume Play; TWS Pairing function; Siri & Google Voice Assistant compatibility, Hands Free Incoming call function; IPX5 Protection class, Led ambient light	
SPECIFICATIONS	
PLL FM Radio	Yes
AM Radio	-
Auto Radio search & Store	Yes
Programme memories	30
CD	-
Remote controler	-
LCD Display	LED Light Soft Button (On/Off, Battery status)
BBS (Bass boost sound)	Yes
Equalizer function	-
Clock	-
Auto ON/OFF	Yes
Amplifier	2.0Ch, 2x30W RMS
Frequency range	80Hz - 16kHz +/- 3dB S/N:>70dB, Distortion: <0,1% 1kHz,1W
MULTIMEDIA	
MP3/WMA/FLAC/WAV/AAC	Yes / - / - / - / -
Other	TWS (True Wireless Stereo)-connect two speakers as a pair for a stronger stereo and surrounding effect ; Siri & Google Voice Assistant compatibility, Hands Free Incoming call function, IPX5 Protection class; Led ambient light



TERMINALS	
AUX-IN / AUX Out	Yes, 3,5mm / -
STEREO HEADPHONE in	No
USB	Yes / MP3 Play
FM Antenna	Yes, Audio cable connection
SD/MMC	-
Power On/Off switch	Soft Button
Wireless MIC / MIC1 / GUITAR	- / - / -
POWER / DIMENSIONS	
Audio Power	2 x 30W RMS (80Hz-16kHz)
Speakers	2x Wide range speakers 3" (7,6cm)
W x H x D unit dimension	366 x 143 x 188 mm
W x H x D box dimension	393 x 169 x 209 mm
Weight Gross/Net	3,10 / 2,85kg
Power	Lithium Battery 3600mAh, 7,4V
Charging	Yes, micro USB connection
ACCESSORIES	
Instruction manual	English, Croatian, Serbian, Macedonian, Albanian, Slovenian + local market languages
Remote controller	-
Accessories	Micro USB-USB Charger cable, Audio AUX 3,5mm cable, User Manual

* Due to different formats and codec format version, it is possible that all specified formats will not be supported. The manufacturer is not responsible for a such problems and it is not considered a malfunction of the device.

* Product specifications are subject to change without notice.